



Sample image

KG160

Type Size: S2

Classification Contact: Rigid contact bridge

Classification Contact Mat: Silver

Classification Terminal: Screw terminal

ated insulation volt	tage Ui					
			Voltage	(V) AC/DC		
			1	000 AC		
ated impulse withs	tand voltage Uimp					
Voltage (kV)	Overvoltage categ	gory Pollution	degree Supply s	ystem		Function
8	III	3	Valid for	lines with grounded common neutral	termination	Switch / Switch disconnector
ated uninterrupted						
Current (A) Ambient temperature (°C)		Peak temperature (°C)	additional requirements			
160		50	55	Ambient temperature +50°C during	24 hours with peaks up to +55°C	
onventional enclos		t Ithe				
Current Ambi (A)	ient temperature (°C)	Peak temperature (°C)	Additional requirements		of stages (from - to) Mounting	Mounting size
160	35	40	Ambient temperature +35° peaks up to +40°C	C during 24 hours with		
ated operational cu	irrent le					
tilization category				Voltage (V)		Current
C-32A				20 - 400		•
C-20A				1000		1
C-21A				20 - 690		1
C-22A				220 - 500		1
C-22A				660 - 690		1
ated operational po	ower		V-14 (1.0)	No of these	No of notes	D/1
tilization category			Voltage (V)	No. of phases	No. of poles	Power (k
C-3 C-3			220 - 240 380 - 440	3	3	
C-3				3	3	
C-3 C-3			500 - 500	3	3	
C-23A			660 - 690 220 - 240	3	3	
C-23A C-23A			380 - 440	3	3	
				3		
C-23A C-23A			500 - 500 660 - 690	3	3	
Iax Fuse Rating IEC			000 - 090	3	3	
iax ruse Rating IEC use characteristic					No. of Fuses	Current
G				,	1	1
JL60947-4-1 , l	UL508					
ated insulation volt	tage Ui					
			Voltage	(V) AC/DC		
				600 AC		
ated thermal curre	nt					
		Current (A)		Ambient temperature (°C)	Additional Text	
		200		0 - 40	ON-OFF switch (Valid when connect Change over switch (Valid when co	

⁻ The operating handle and position indicating means to be used with these manual motor controllers should be provided from the manufacturer, or the operating handle and position indicating means to be used should have been previously evaluated in combination with the manual motor controllers.



tated insulation voltage Ui						
		Voltage (V) AC / DC				
Rated thermal current		600 AC				
	Current (A)	Ambient ter	mperature (°C) Additional Text		
	200		0 -	40 -		
GENERAL TECHNICAL INFORMATION						
ightening torque of screws						
	tighte	ening torque (Nm)			tigh	tening torque (lb
Rated short-time withstand current lcw		14				•
		Time (s)				Current
Size of conductor		1				30
composition of conductor	Min. / Max. value	No. of conductor per	terminal	Cross section (mm²) or	Material of th	e wire
colid wire	Min.	no. or conductor per		(AWG/kcmil) 6mm²	Copper	· · · · · ·
lexible wire	Max.			70mm ²	Copper	
lexible wire	Min.			16mm²	Copper	
lexible wire	Max.			AWG 2/0	Copper	
Single-core or stranded wire	Max.			95mm²	Copper	
Single-core or stranded wire	Max.			AWG 3/0	Copper	
lexible wire with sleeve	Max.		1	70mm²	Copper	
lexible wire with ferrule according to DIN 46228	Min.		1	10mm²	Copper	
Approbations						
Specification						Marking
AC						EHC
DE marking						C€
g						66
JK Directives						
EC 60947-3; EN 60947-3; VDE 0660 Teil107						IEC 60947
0, 100						EN 60947
50 (00 47 (4						IEC 60947
EC 60947-6-1						EN 60947
						_
JL 60947-4-1; CSA C22.2 No. 60947-4-1						CUL) US LISTED7787
SSA C.22.2 No.14						® ®
GB/T14048.3						(1)
						GB/T14048.3
Power loss per pole						Power
Conditions during transport and storing						
Minimum temp	perature (°C)	Maximum ter	mperature (°C) additional requirements		
	-40			85 In case of temperatures		k load permissil

- Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology.
- Use copper wire only. Do not coat the wire end with tin.
- Terminals with factory fitted jumper links are tightened during production. Take care during installation to ensure factory fitted links are not lost by undoing both sides of linked terminals. After wiring, all terminal screws must be tightened to recommended torque specifications.

Operating temperature	
Min. Temperature [°C]	Max. Temperature [°C]
-5	55